



The Wireless Terminal is used as a Workstation Terminal in several Qmatic systems. It is a handheld device and can be worn with a built-in belt clip and/or a neck ribbon.

It is used with the *INTERFACE MULTI I/O \* 8 + RF-MOD.433MHZ.*

The Wireless Terminal can also be used to remotely control functions like open doors and issue tickets.

**Features**

- Wireless – easy to install – no hardwiring
- Three switches
- Power saving and auto shut off
- Ergonomic and contemporary design

**With the Wireless Terminal you can**

- Call customers
- Close the Workstation
- Send alarms
- Remotely control functions like open doors and issue tickets

**Used with**

<b>Q-WIN 55.01 P and later</b>	<b>Solo</b>	<b>Solo Linea</b>	<b>Duet</b>	<b>INTERFACE MULTI I/O * 8 + RF-MOD.433MHZ</b>
X	X	X	X	X

**Technical specifications**

Dimensions: Diameter x Thickness	70 X 21 mm
Weight incl. Batteries	125 g
Material, casing	Plastic
Batteries	4 pcs of either AAA 1.5 V or AAA 1.2 V rechargeable
Power consumption	12 mA maximum
Output power	10 mW EU, 1 mW USA
Frequency	433.92 MHz
Range (in the open)	30 m
Temperature	Operating: 10 – 30°C, storage: -10 – 40°C
Humidity, relative	Operating: 15 – 85%, storage: 10 – 90%
Safety and other regulations	CE, RoHS, WEEE
EU: CE marked and complies with the following standards:	ETSI/EN300220 and EN301489
USA: complies with the following standards:	FCC 15.231 and FCC ID: RT2- 10320211

**The package contains**

Wireless Terminal	1
AAA 1.5 V batteries	4

**Article number**

EU 433.92 MHz	10320203
USA 433.92 MHz	10320211